

OPERATING INSTRUCTIONS FOR CHINO AH3000 MULTIPOINT

STEP	OPERATION	DISPLAY
TO TURN POINTS ON		
1	press SHIFT and 7 at the same time	R 0 1 : 2 3 1 0 / 2 4 9 0
2	press SET, cursor will move under point number	R 0 1 : 2 3 1 0 / 2 4 9 0
3	enter desired 2 diget point number (07)	R 0 7 : 2 3 1 0 / 2 4 9 0
4	enter the number 2, cursor moves and enter 3 this is the factory programed temperature range	R 0 7 : 2 3 1 0 / 2 4 9 0
5	enter number 1(this sets the RJ factor)	R 0 7 : 2 3 1 0 / 2 4 9 0
6	enter 0 (low end of scale)	R 0 7 : 2 3 1 0 / 2 4 9 0
7	press SHIFT and MINUS(-) this will enter the back slash looking symbol.	R 0 7 : 2 3 1 0 / 2 4 9 0
8	enter 2 then 4 then 9 then 0, cursor will move with each entry. (high end of scale).	R 0 7 : 2 3 1 0 / 2 4 9 0
	enter 1370 for C scale	R 0 7 : 2 3 1 0 / 1 3 7 0
9	press entry.	
10	repeat steps 3 through 9 till all points are on that you need to use	
11	press SHIFT and SET at the same time	
12	press DISPLAY to start program and return to running display	

NOTE if everything is correct for the point number selected just press the ENTRY and move to next point

TO CHANGE FROM F TO C

- | | | |
|---|---|---|
| 1 | press and hold SHIFT and > at the same time for
for 3 to 4 seconds | d E G . C / d E G . F d E G . F or C |
| 2 | press SET cursor will appear under the third d | d E G . C / d E G . F d E G . F or C |
| 3 | press the up arrow to change from F to C | d E G . C / d E G . F d E G . C or F |
| 4 | press ENTRY | |
| 5 | Press DISPLAY to return to running display | |

NOTE points must be turned on as shown above when you change scale

TO TURN POINTS OFF

- | | | |
|---|--|---------------------------|
| 1 | press SHIFT and 7 at the same time | R 0 7 : 2 3 1 0 / 2 4 9 0 |
| 2 | press SET, cursor will be under point number | R 0 7 : 2 3 1 0 / 2 4 9 0 |
| 3 | use up or down arrow to show the point number you want to shut off | |
| 4 | press SHIFT and 0 at the same time | R |
| 5 | press ENTRY | |
| 6 | repeat steps 3 through 5 until all undesired points are turned off | |
| 7 | press SHIFT and SET at the same time | |
| 8 | press DISPLAY to return to running display | |